

FEATURES & BENEFITS



replaceable die for system H1



crimping shape: "hexagon"

NOTE!

On special request we can provide dies for other purposes.



Type	Index Ergom	Socket code no.	Cable cross-section [mm²]	Terminal group	Crimping shape
AH1-19	E06PZ-05090300100	19	120	Al-c	hexagon
AH1-20	E06PZ-05090300200	20	70	Al-g	hexagon
AH1-21	E06PZ-05090300300	21	150	Al-c	hexagon
AH1-22	E06PZ-05090300400	22	95	Al-g	hexagon
		22	95-120	Al DIN	
		22	95-120	Al-Cu	
AH1-23	E06PZ-05090300500	23	185	Al-c	hexagon
AH1-25	E06PZ-05090300600	25	120	Al-g	hexagon
		25	150	Al DIN	
		25	150	Al-Cu	
AH1-28	E06PZ-05090300700	28	240	Al-c	hexagon
		28	150	Al-g	
		28	185	Al DIN	
		28	185	Al-Cu	
AH1-30	E06PZ-05090300800	30	185	Al-g	hexagon
AH1-32	E06PZ-05090300900	32	240	Al DIN	hexagon
		32	240	Al-Cu	
AH1-34	E06PZ-05090301000	34	240	Al-g	hexagon
		34	300	Al DIN	
		34	300	Al-Cu	
AH1-38	E06PZ-05090301100	38	400	Al DIN	hexagon
AH1-44	E06PZ-05090301200	44	500	Al DIN	hexagon
AH1-52	E06PZ-05090301300	52	625	Al DIN	hexagon
AH1-58	E06PZ-05090301400	58	800	Al DIN	hexagon
RH1-19	E06PZ-05090200150	19	120	Standard Cu	hexagon
RH1-20	E06PZ-05090200200	20	150	Standard Cu	hexagon
		20	120	Cu DIN	
RH1-22	E06PZ-05090200300	22	150	Cu DIN	hexagon
RH1-23	E06PZ-05090200400	23	185	Standard Cu	hexagon
RH1-25	E06PZ-05090200500	25	240	Standard Cu	hexagon
		25	185	Cu DIN	
RH1-28	E06PZ-05090200700	28	300	Standard Cu	hexagon
		28	240	Cu DIN	
RH1-32	E06PZ-05090200800	32	400	Standard Cu	hexagon
		32	300	Cu DIN	
RH1-36	E06PZ-05090201000	36	500	Standard Cu	hexagon
RH1-38	E06PZ-05090201100	38	400	Cu DIN	hexagon
RH1-42	E06PZ-05090201200	42	500	Cu DIN	hexagon
		42	625	Standard Cu	
RH1-44	E06PZ-05090201300	44	625	Cu DIN	hexagon
RH1-52	E06PZ-05090201400	52	800	Cu DIN	hexagon
RH1-58	E06PZ-05090201500	58	1000	Cu DIN	hexagon